

ASCII Values of Characters



MARCH 2013

Two useful functions



- `ord(ch)`
if `ch` is a single character string, this function returns the ASCII code for `ch`
- `chr(i)`
returns a string of one character whose ASCII code is the integer `i`

What is ASCII?

It stands for the *American Standard Code for Information Interchange*. It assigns a number in the range 0..255 to every character that can be entered at the keyboard.

More on ASCII



- The numbers 0..31 are reserved for unprintable characters, e.g., the tab character ("\\t"), the end of line character ("\\n"), etc.
- 32 is the ASCII value of the space character (" ")
- 33..47 is used for some punctuation characters
- 48..57 is used for digits “0” through “9”
- 65..90 is used for upper case letters
- 97..122 is used for lower case letters

ASCII Table



| Dec | Hx | Oct | Char | | Dec | Hx | Oct | Html | Chr | | Dec | Hx | Oct | Html | Chr | | Dec | Hx | Oct | Html | Chr |
|-----|----|-----|------------|--------------------------|-----|----|-----|-------|--------------|--|-----|----|-----|-------|----------|--|-----|----|-----|--------|------------|
| 0 | 0 | 000 | MUL | (null) | 32 | 20 | 040 | | Space | | 64 | 40 | 100 | @ | Ø | | 96 | 60 | 140 | ` | ` |
| 1 | 1 | 001 | SOH | (start of heading) | 33 | 21 | 041 | ! | ! | | 65 | 41 | 101 | A | A | | 97 | 61 | 141 | a | a |
| 2 | 2 | 002 | STX | (start of text) | 34 | 22 | 042 | " | " | | 66 | 42 | 102 | B | B | | 98 | 62 | 142 | b | b |
| 3 | 3 | 003 | ETX | (end of text) | 35 | 23 | 043 | # | # | | 67 | 43 | 103 | C | C | | 99 | 63 | 143 | c | c |
| 4 | 4 | 004 | EOT | (end of transmission) | 36 | 24 | 044 | $ | \$ | | 68 | 44 | 104 | D | D | | 100 | 64 | 144 | d | d |
| 5 | 5 | 005 | ENQ | (enquiry) | 37 | 25 | 045 | % | % | | 69 | 45 | 105 | E | E | | 101 | 65 | 145 | e | e |
| 6 | 6 | 006 | ACK | (acknowledge) | 38 | 26 | 046 | & | & | | 70 | 46 | 106 | F | F | | 102 | 66 | 146 | f | f |
| 7 | 7 | 007 | BEL | (bell) | 39 | 27 | 047 | ' | ' | | 71 | 47 | 107 | G | G | | 103 | 67 | 147 | g | g |
| 8 | 8 | 010 | BS | (backspace) | 40 | 28 | 050 | (| (| | 72 | 48 | 110 | H | H | | 104 | 68 | 150 | h | h |
| 9 | 9 | 011 | TAB | (horizontal tab) | 41 | 29 | 051 |) |) | | 73 | 49 | 111 | I | I | | 105 | 69 | 151 | i | i |
| 10 | A | 012 | LF | (NL line feed, new line) | 42 | 2A | 052 | * | * | | 74 | 4A | 112 | J | J | | 106 | 6A | 152 | j | j |
| 11 | B | 013 | VT | (vertical tab) | 43 | 2B | 053 | + | + | | 75 | 4B | 113 | K | K | | 107 | 6B | 153 | k | k |
| 12 | C | 014 | FF | (NP form feed, new page) | 44 | 2C | 054 | , | , | | 76 | 4C | 114 | L | L | | 108 | 6C | 154 | l | l |
| 13 | D | 015 | CR | (carriage return) | 45 | 2D | 055 | - | - | | 77 | 4D | 115 | M | M | | 109 | 6D | 155 | m | m |
| 14 | E | 016 | SO | (shift out) | 46 | 2E | 056 | . | . | | 78 | 4E | 116 | N | N | | 110 | 6E | 156 | n | n |
| 15 | F | 017 | SI | (shift in) | 47 | 2F | 057 | / | / | | 79 | 4F | 117 | O | O | | 111 | 6F | 157 | o | o |
| 16 | 10 | 020 | DLE | (data link escape) | 48 | 30 | 060 | 0 | Ø | | 80 | 50 | 120 | P | P | | 112 | 70 | 160 | p | p |
| 17 | 11 | 021 | DC1 | (device control 1) | 49 | 31 | 061 | 1 | 1 | | 81 | 51 | 121 | Q | Q | | 113 | 71 | 161 | q | q |
| 18 | 12 | 022 | DC2 | (device control 2) | 50 | 32 | 062 | 2 | 2 | | 82 | 52 | 122 | R | R | | 114 | 72 | 162 | r | r |
| 19 | 13 | 023 | DC3 | (device control 3) | 51 | 33 | 063 | 3 | 3 | | 83 | 53 | 123 | S | S | | 115 | 73 | 163 | s | s |
| 20 | 14 | 024 | DC4 | (device control 4) | 52 | 34 | 064 | 4 | 4 | | 84 | 54 | 124 | T | T | | 116 | 74 | 164 | t | t |
| 21 | 15 | 025 | NAK | (negative acknowledge) | 53 | 35 | 065 | 5 | 5 | | 85 | 55 | 125 | U | U | | 117 | 75 | 165 | u | u |
| 22 | 16 | 026 | SYN | (synchronous idle) | 54 | 36 | 066 | 6 | 6 | | 86 | 56 | 126 | V | V | | 118 | 76 | 166 | v | v |
| 23 | 17 | 027 | ETB | (end of trans. block) | 55 | 37 | 067 | 7 | 7 | | 87 | 57 | 127 | W | W | | 119 | 77 | 167 | w | w |
| 24 | 18 | 030 | CAN | (cancel) | 56 | 38 | 070 | 8 | 8 | | 88 | 58 | 130 | X | X | | 120 | 78 | 170 | x | x |
| 25 | 19 | 031 | EM | (end of medium) | 57 | 39 | 071 | 9 | 9 | | 89 | 59 | 131 | Y | Y | | 121 | 79 | 171 | y | y |
| 26 | 1A | 032 | SUB | (substitute) | 58 | 3A | 072 | : | : | | 90 | 5A | 132 | Z | Z | | 122 | 7A | 172 | z | z |
| 27 | 1B | 033 | ESC | (escape) | 59 | 3B | 073 | ; | : | | 91 | 5B | 133 | [| [| | 123 | 7B | 173 | { | { |
| 28 | 1C | 034 | FS | (file separator) | 60 | 3C | 074 | < | < | | 92 | 5C | 134 | \ | \ | | 124 | 7C | 174 | | | |
| 29 | 1D | 035 | GS | (group separator) | 61 | 3D | 075 | = | = | | 93 | 5D | 135 |] |] | | 125 | 7D | 175 | } | } |
| 30 | 1E | 036 | RS | (record separator) | 62 | 3E | 076 | > | > | | 94 | 5E | 136 | ^ | ^ | | 126 | 7E | 176 | ~ | ~ |
| 31 | 1F | 037 | US | (unit separator) | 63 | 3F | 077 | ? | ? | | 95 | 5F | 137 | _ | _ | | 127 | 7F | 177 | | DEL |

Some examples of chr and ord in action



```
>>> ord("a")
97
>>> chr(97)
'a'
>>> ord(" ")
32
>>> ord("o")
48
>>> chr(48)
'o'
>>> chr(49)
'1'
>>> ord("A")
65
>>> ord("B")
66
```

How are these functions useful?



- Because of the fact that all the upper case letters occur consecutively in the ASCII table, the expression `ord(ch) - ord("A")` has value 0 for `ch = "A"`, value 1 for `ch = "B"`, has value 2 for `ch = "C"`, etc.
- Similarly, `ord(ch)-ord("a")` has value 0 for `ch = "a"` , has value 1 for `ch = "b"`, has value 2 for `ch = "c"`, etc.

A program to count letter frequencies



```
f = open("war.txt")
L = [0]*26
s = f.read()
for ch in s:
    if ch.isupper():
        L[ord(ch)-ord("A")] = L[ord(ch)-ord("A")] + 1
    elif ch.islower():
        L[ord(ch)-ord("a")] = L[ord(ch)-ord("a")] + 1
print L
```

Notice how `ord(ch)-ord("A")` and `ord(ch)-ord("a")` are used to index into the list `L`.

Another Example



Write a function that takes a nonnegative integer (in decimal representation) and returns a string that is the hexadecimal equivalent of the given nonnegative integer.